

ARTICLE 130 – WORK INVOLVING ELECTRICAL HAZARDS

**Table 130.5(C) Estimate of the Likelihood of Occurrence of an Arc Flash Incident for ac and dc Systems**

Task	Equipment Condition <sup>a</sup>	Likelihood of Occurrence <sup>b</sup>
Reading a panel meter while operating a meter switch. Performing infrared thermography and other non-contact inspections outside the restricted approach boundary. This activity does not include opening of doors or covers. Working on control circuits with exposed energized electrical conductors and circuit parts, nominal 125 volts ac or dc, or below without any other exposed energized equipment over nominal 125 volts ac or dc, including opening of hinged covers to gain access. Examination of insulated cable with no manipulation of cable. For dc systems, maintenance on a single cell of a battery system or multi-cell units in an open rack.	Any	No
For ac systems, work on energized electrical conductors and circuit parts, including electrical testing. Operation of a CB or switch the first time after installation or completion of maintenance in the equipment. For dc systems, working on energized electrical conductors and circuit parts of series-connected battery cells, including electrical testing. Removal or installation of CBs or switches. Opening hinged door (s) or cover(s) or removal of bolted covers (to expose bare, energized electrical conductors and circuit parts). For dc systems, this includes bolted covers, such as battery terminal covers. Application of temporary protective grounding equipment, after voltage test. Working on control circuits with exposed energized electrical conductors and circuit parts, greater than 120 volts. Insertion or removal of individual starter buckets from motor control center (MCC). Insertion or removal (racking) of circuit breakers (CBs) or starters from cubicles, doors open or closed. Insertion or removal of plug-in devices into or from busways. Examination of insulated cable with manipulation of cable. Working on exposed energized electrical conductors and circuit parts of equipment directly supplied by a panelboard or motor control center. Insertion or removal of revenue meters (kW-hour; at primary voltage and current). Insertion or removal of covers for battery intercell connector(s). For dc systems, working on exposed energized electrical conductors and circuit parts of utilization equipment directly supplied by a dc source. Opening voltage transformer or control power transformer compartments. Operation of outdoor disconnect switch (hookstick operated) at 1 kV through 15 kV. Operation of outdoor disconnect switch (gang-operated, from grade) at 1 kV through 15 kV.	Any	Yes
Operation of a CB, switch, contactor, or starter. Voltage testing on individual battery cells or individual multi-cell units. Removal or installation of covers for equipment such as wireways, junction boxes, and cable trays that does not expose bare, energized electrical conductors and circuit parts. Opening a panelboard hinged door or cover to access dead front overcurrent devices. Removal of battery nonconductive intercell connector covers.	Normal	No

ARTICLE 130 – WORK INVOLVING ELECTRICAL HAZARDS

Maintenance and testing on individual battery cells or individual multi-cell units in an open rack.	Abnormal	Yes
Insertion or removal of individual cells or multi-cell units of a battery system in an open rack.		
Arc—resistant equipment with the <b>DOORS CLOSED</b> and <b>SECURED</b> , and where the available fault current and fault clearing time does not exceed that of the arc-resistant rating of the equipment in one of the following conditions:		
(1) Insertion or removal of individual starter buckets		
(2) Insertion or removal (racking) of CBs from cubicles		
(3) Insertion or removal (racking) of ground and test device		
(4) Insertion or removal (racking) of voltage transformers on or off the bus		

<sup>a</sup> Equipment is considered to be in a “normal operating condition” if all of the conditions in 110.4(D) are satisfied.

<sup>b</sup> As defined in this standard, the two components of risk are the likelihood of occurrence of injury or damage to health and the severity of injury or damage to health that results from a hazard. Risk assessment is an overall process that involves estimating both the likelihood of occurrence and severity to determine if additional protective measures are required. The estimate of the likelihood of occurrence contained in this table does not cover every possible condition or situation, nor does it address severity of injury or damage to health. Where this table identifies “No” as an estimate of likelihood of occurrence, it means that an arc flash incident is not likely to occur. Where this table identifies “Yes” as an estimate of likelihood of occurrence, it means an arc flash incident should be considered likely to occur. The likelihood of occurrence must be combined with the potential severity of the arcing incident to determine if additional protective measures are required to be selected and implemented according to the hierarchy of risk control identified in 110.5(H) (3).

Informational Note No. 1: An example of a standard that provides information for arc-resistant equipment referred to in Table 130.5(0) is IEEE 03720.7, *Guide for Testing Switchgear Rated bit: to 52 kV for Internal Airing Faults*.

Informational Note No. 2: Improper or inadequate maintenance can result in increased fault clearing time of the overcurrent protective device, thus increasing the incident energy. Where equipment is not properly installed or maintained, PPE selection based on incident energy analysis or the PPE category method might not provide adequate protection from are flash hazards.

Informational Note No. 3: Both larger and smaller available fault currents could result in higher incident energy. If the available fault current increases without a decrease in the fault clearing time of the overcurrent protective device, the incident energy will increase. If the available fault current decreases, resulting in a longer fault clearing time for the overcurrent protective device, incident energy could also increase.

Informational Note No. 4: The occurrence of an arcing fault inside an enclosure produces a variety of physical phenomena very different from a bolted fault. For example, the are energy resulting from an are developed in the air will cause a sudden pressure increase and localized overheating. Equipment and design practices are available to minimize the energy levels and the number of procedures that could expose an employee to high levels of incident energy. Proven designs such as arc-resistant switchgear, remote racking (insertion or removal), remote opening and closing of switching devices, high-resistance grounding of low-voltage and 5000-volt (nominal) systems, current limitation, and specification of covered bus or covered conductors within equipment are available to reduce the risk associated with an arc flash incident. See Informative Annex O for safety-related design requirements. Informational Note No. 5: For additional direction for performing maintenance on overcurrent protective devices, see Chapter 2, Safety-Related Maintenance Requirements.

Informational Note No. 6: See IEEE 1584, *Guide for Performing Air Flash Hazard Calculations*, for more information regarding incident energy and the arc flash boundary for three-phase systems.